

Voltage Stabilisers



Founded in 1969, ORTEA SpA is a leading company in manufacturing and engineering voltage stabilisers and magnetic components.

Over forty years in the business and ongoing technical research have made of ORTEA a competitive and technologically advanced company. Close co-operation between design, production and marketing enables to meet the requirements of a constantly growing number of customers.

In 1996 ORTEA joined ICAR Group, made of Italian and European industrial units specialised in manufacturing capacitors and power factor correction systems.

Beside standard production, ORTEA can be extremely flexible in developing and manufacturing special equipment according to User's specification. All this thanks to the experience gained over many years of applied technological development.

Such development includes IT tools that enable the technical staff to elaborate electrical and mechanical designs for each «custom product» on a quick and cost-effective basis.



The belief that product quality and Customer satisfaction are the core of a modern organisation, led to the implementation of an ISO9001:2008 certified Company Managing System.

The achievement of the ISO14001:2004 and OHSAS18001:2007 accreditation was a natural integration in order to optimise the Company's performance, showing at the same time the commitment towards environmental and safety at work issues.



ISO 9001 • ISO 14001
OHSAS 18001



CERTIFICATE OF APPROVAL
This is to certify that the Quality, Environmental and Occupational Health & Safety Management System of:

Ortea S.p.A.
Via dei Chiosi, 21
20873 Cavenago Brianza (Monza e della Brianza) – Italia

has been approved by Lloyd's Register Quality Assurance to the following Management System Standard:

ISO 9001:2008
ISO 14001:2004
OHSAS 18001:2007

The Quality, Environmental and Occupational Health & Safety Management System is applied to:

Design of...



ORTEA is well established in the global market. Thanks to strategically positioned offices and distributors and efficient commercial relations, ORTEA's products are installed and working in a large number of countries.



- ▲ ORTEA headquarters (Italy)
- ▲ ORTEA branches (Russia, Ivory Coast, Kenya, Venezuela)



three-phase
30-1250kVA



Standard features

Voltage stabilisation	Independent phase control
PC selectable output voltage*	from 210 to 255V (L-N) from 360 to 440V (L-L)
Frequency	50/60Hz $\pm 5\%$
Admitted load variation	Up to 100%
Admitted load imbalance	100%
Cooling	Natural air ventilation. Up to 35°C aided with fans
Ambient temperature	-25/+45°C
Storage temperature	-25/+60°C
Max relative humidity	95%
Admitted overload	200% 2 min.
Harmonic distortion	None introduced
Colour	RAL 7035
Protection degree	IP21
Instrumentation	Input & output digital multimeter
Installation	Indoor
Overvoltage protection	– Class II output surge arrester – Optimal voltage return through supercapacitors – in case of blackout

* The output voltage can be adjusted by choosing **one** of the indicated values. Such choice sets the new nominal value as a reference for all the stabiliser parameters.

Accessories

Interrupting devices
Load protection against over/undervoltage
Manual by-pass line
Total protection kit
Input isolating transformer
Integrated automatic power factor correction system
SPD surge arrester
EMI/RFI filters
Neutral point reactor
IP54 protection degree for indoor and outdoor installation



All ORTEA stabilisers are designed and built in compliance with the Low Voltage and Electromagnetic Compatibility European Directives with regard to the CE marking requirements. ORTEA products are built with suitable quality components and that the manufacturing process is constantly verified in accordance with the Quality Control Plans which the Company applies in compliance with the ISO 9001:2008 Standards. The commitment towards environmental issues and safety at work matters is guaranteed by the certification of the Management System according to the ISO14001:2004 and OHSAS18001:2007 Standards. In order to obtain better performance, the products described in the present document can be altered by the Company at any date and without prior notice. Technical data and descriptions do hold therefore any contractual value.

Orion Plus three-phase 30-1250kVA

Rating in relation to the input variation percentage

±15%	±20%	±25%	±30%	+15%/-35%	+15%/-45%
80	60	45	30	45	30
105	80	60	45	60	45
135	105	80	60	80	60
150	120	90	80	90	80
175	135	105	90	105	90
200	150	120	105	120	105
250	175	135	120	135	120
320	250	200	150	200	150
400	300	250	200	250	200
500	400	300	250	300	250
630	500	400	300	400	300
800	630	500	400	500	400
1000	800	630	500	630	500
1250	1000	800	630	800	630

Orion Plus stabilisers are available for different ranges of input voltage fluctuation. In the ±15%/ ±20% and ±25%/ ±30% types, the change of input range is obtained through different internal connections.

The Orion Plus voltage stabilisers regulate the output voltage **independently on each phase**.

Similarly to the Orion stabilisers, they can supply **any single-phase, bi-phase and three-phase load** even in case of and up to **100% unbalanced load current** and asymmetrical mains distribution.

In this configuration, the presence of **the neutral wire is required**. The stabiliser can also operate without neutral wire by adding a device able to generate it (D/zn or D /yn isolating transformer or neutral point reactor).

The stabilisers are cooled via **natural air ventilation**, assisted by extracting fans when the cabinet internal temperature exceeds 35°C).

The instrumentation consists of **two multi-task digital line analysers** which are able to provide with information regarding the status of the lines upstream and downstream the voltage stabiliser (phase and linked voltages, current, power factor, active power, apparent power, reactive power, etc.)

The operating status of the stabiliser can be **monitored** by means of the **LEDs** on the front panel displaying all the **information** regarding each phase operating mode ('power on'; reaching of voltage regulation limits; increase/decrease of voltage regulation) and the possible **alarms** (minimum and maximum voltage, maximum current: overtemperature; ventilation failure). The alarm indicators are accompanied by an acoustic alarm.

– Up to 250kVA ±15%, the regulation circuit is protected against overload and short circuit on the voltage regulator by an **automatic circuit breaker**.

– From 300kVA ±15%, an **electronic voltage regulator protection system** activates in case of overload on the voltage regulator. In such condition, the load supply is not interrupted, but the stabiliser output voltage is automatically set to the lower between the mains voltage and the pre-set output voltage.

The service continuity is guaranteed, although the voltage is not stabilised. When the overload condition ceases to exist, the stabiliser switches automatically back to regular functioning.

The auxiliary circuits are protected by **fuses**.

The control logic, performed on the **true RMS** value, is based on **DSP microprocessors**.

The unit parameters and the output voltage reference can be **set** by using a **personal computer**, thus allowing for dealing directly in the field with any problems related to voltage stability.


All Orion Plus stabilisers are provided with **Class II SPD surge arrestors**.



Orion Plus

three-phase

30-1250kVA



Wide range

- symmetrical: **±15%, ±20%, ±25%, ±30%** (other on request)
 - asymmetrical: **+15%/-35%, +15%/-45%** (other on request)
- Output voltage accuracy: **±0.5%**.




Technology

Control and stabilisation, performed on the **true RMS** value, are based on a digital **microprocessor** operating with a software specifically developed for Ortea.

Parameters and reference voltage can be **set** via a **PC**, thus allowing for adjusting the stabiliser to the actual site conditions.

Independent regulation on each phase.



Long life

Ortea system voltage regulator with **rollers** (without brushes, which are subject to heavy wear & tear). Depending on the rating, the voltage regulator could be **toroidal** or **columnar**.



Protection

Up to 250kVA ±15%: The voltage regulator is protected by a three-phase automatic **circuit breaker**.

The auxiliary circuit is protected by **fuses**.

Overvoltage protection: Class II output **surge arrester**.



Protection

From 300kVA ±15%: The stabiliser is provided of an **electronic** voltage regulator **protection system** activates in case of overload on the voltage regulator. In such conditions, the **load supply is not interrupted**.

The auxiliary circuit is protected by **fuses**.

Overvoltage protection: Class II output **surge arrester**.



Protection

Output voltage reset to the minimum value in case of blackout by means of **supercapacitors** banks in order to ensure the correct shutdown.



Instrumentation

Two **multi-task digital analyser** mounted on the front panel (linked and phase voltage current, frequency, power factor, active power, reactive power, apparent power etc.).



Monitoring

The stabiliser **operating mode** can be easily **monitored** by means of the **LEDs** on the front panel, which provide with **information** and **alarms**.

Orion Plus

three-phase
30-1250kVA

Type	Input voltage variation range	Rating	Input voltage range	Maximum input current	Output voltage $\pm 0.5\%$	Output current	Efficiency	Speed regulation	Cabinet	Weight
	[%]	[kVA]	[V]	[A]	[V]	[A]	[%]	[ms/V]	Type	[kg]

Input voltage variation range $\pm 20\%/\pm 15\%$ (the values listed in the table are referred to 400V nominal voltage)

60-20	± 20	60	320-480	109		86		12		
80-15	± 15	80	340-460	136	400	116	>98	16	51	430
80-20	± 20	80	320-480	145		116		12		
105-15	± 15	105	340-460	179	400	152	>98	16	51	490
105-20	± 20	105	320-480	190		152		12		
135-15	± 15	135	340-460	229	400	195	>98	16	51	580
120-20	± 20	120	320-480	216		173		14		
150-15	± 15	150	340-460	255	400	217	>98	18	55	710
135-20	± 20	135	320-480	244		195		14		
175-15	± 15	175	340-460	298	400	253	>98	18	55	760
150-20	± 20	150	320-480	271		217		14		
200-15	± 15	200	340-460	340	400	289	>98	18	55	850
175-20	± 20	175	320-480	316		253		14		
250-15	± 15	250	340-460	425	400	361	>98	18	55	950
250-20	± 20	250	320-480	446		361		15		
320-15	± 15	320	340-460	544	400	462	>98	20	55	850
300-20	± 20	300	320-480	543		434		15		
400-15	± 15	400	340-460	680	400	578	>98	20	55	1100
400-20	± 20	400	320-480	723		578		15		
500-15	± 15	500	340-460	851	400	723	>98	20	53	1400
500-20	± 20	500	320-480	904		723		15		
630-15	± 15	630	340-460	1071	400	910	>98	20	67	1600
630-20	± 20	630	320-480	1138		910		18		
800-15	± 15	800	340-460	1360	400	1156	>98	24	62	2000
800-20	± 20	800	320-480	1445		1156		18		
1000-15	± 15	1000	340-460	1700	400	1445	>98	24	62	2200
1000-20	± 20	1000	320-480	1806		1445		18		
1250-15	± 15	1250	340-460	2125	400	1806	>98	24	63	2400

Orion Plus

three-phase
30-1250kVA

Type	Input voltage variation range	Rating	Input voltage range	Maximum input current	Output voltage $\pm 0.5\%$	Output current	Efficiency	Speed regulation	Cabinet	Weight
	[%]	[kVA]	[V]	[A]	[V]	[A]	[%]	[ms/V]	Type	[kg]

Input voltage variation range $\pm 30\%/\pm 25\%$ (the values listed in the table are referred to 400V nominal voltage)

30-30	± 30	30	280-520	61		43		8		
45-25	± 25	45	300-500	86	400	65	>98	10	51	430
45-30	± 30	45	280-520	93		65		8		
60-25	± 25	60	300-500	116	400	87	>98	10	51	490
60-30	± 30	60	280-520	124		87		8		
80-25	± 25	80	300-500	155	400	116	>98	10	51	580
80-30	± 30	80	280-520	166		116		9		
90-25	± 25	90	300-500	173	400	130	>98	11	55	710
90-30	± 30	90	280-520	185		130		9		
105-25	± 25	105	300-500	203	400	152	>98	11	55	760
105-30	± 30	105	280-520	217		152		9		
120-25	± 25	120	300-500	231	400	173	>98	11	55	850
120-30	± 30	120	280-520	247		173		9		
135-25	± 25	135	300-500	260	400	195	>98	11	55	950
150-30	± 30	150	280-520	310		217		10		
200-25	± 25	200	300-500	385	400	289	>98	12	55	1200
200-30	± 30	200	280-520	413		289		10		
250-25	± 25	250	300-500	481	400	361	>98	12	55	1300
250-30	± 30	250	280-520	515		361		10		
300-25	± 25	300	300-500	579	400	434	>98	12	53	1400
300-30	± 30	300	280-520	620		434		10		
400-25	± 25	400	300-500	771	400	578	>98	12	67	1600
400-30	± 30	400	280-520	826		578		12		
500-25	± 25	500	300-500	963	400	723	>98	15	62	2000
500-30	± 30	500	280-520	1032		723		12		
630-25	± 25	630	300-500	1214	400	910	>98	15	62	2200
630-30	± 30	630	280-520	1300		910		12		
800-25	± 25	800	300-500	1541	400	1156	>98	15	63	2400

Orion Plus

three-phase
30-1250kVA

Type	Input voltage variation range	Rating	Input voltage range	Maximum input current	Output voltage $\pm 0.5\%$	Output current	Efficiency	Speed regulation	Cabinet	Weight
	[%]	[kVA]	[V]	[A]	[V]	[A]	[%]	[ms/V]	Type	[kg]

Input voltage variation range **+15%/-35%** (the values listed in the table are referred to 400V nominal voltage)

45-15/35	+15/-35	45	260-460	100	400	65	>98	10	51	470
60-15/35	+15/-35	60	260-460	134	400	87	>98	10	51	550
80-15/35	+15/-35	80	260-460	178	400	116	>98	10	51	600
90-15/35	+15/-35	90	260-460	200	400	130	>98	11	55	850
105-15/35	+15/-35	105	260-460	234	400	152	>98	11	55	950
120-15/35	+15/-35	120	260-460	266	400	173	>98	11	55	1050
135-15/35	+15/-35	135	260-460	300	400	195	>98	11	55	1200
200-15/35	+15/-35	200	260-460	445	400	289	>98	12	55	1500
250-15/35	+15/-35	250	260-460	555	400	361	>98	12	52	1650
300-15/35	+15/-35	300	260-460	668	400	434	>98	12	52	1750
400-15/35	+15/-35	400	260-460	889	400	578	>98	12	62	2100
500-15/35	+15/-35	500	260-460	1111	400	723	>98	15	63	2900
630-15/35	+15/-35	630	260-460	1400	400	910	>98	15	63	3050
800-15/35	+15/-35	800	260-460	1778	400	1156	>98	15	64	3800

Input voltage variation range **+15%/-45%** (the values listed in the table are referred to 400V nominal voltage)

30-15/45	+15/-45	30	220-460	78	400	43	>98	8	51	470
45-15/45	+15/-45	45	220-460	118	400	65	>98	8	51	550
60-15/45	+15/-45	60	220-460	158	400	87	>98	8	51	600
80-15/45	+15/-45	80	220-460	211	400	116	>98	9	55	850
90-15/45	+15/-45	90	220-460	236	400	130	>98	9	55	950
105-15/45	+15/-45	105	220-460	276	400	152	>98	9	55	1050
120-15/45	+15/-45	120	220-460	315	400	173	>98	9	55	1250
150-15/45	+15/-45	150	220-460	395	400	217	>98	10	55	1450
200-15/45	+15/-45	200	220-460	525	400	289	>98	10	52	1650
250-15/45	+15/-45	250	220-460	656	400	361	>98	10	52	1800
300-15/45	+15/-45	300	220-460	789	400	434	>98	10	62	2200
400-15/45	+15/-45	400	220-460	1051	400	578	>98	12	63	3000
500-15/45	+15/-45	500	220-460	1315	400	723	>98	12	63	3200
630-15/45	+15/-45	630	220-460	1655	400	910	>98	12	64	4000



Via dei Chiosi, 21
20873 Cavenago di Brianza MB - ITALY
Phone: +39.02.95.917.800
Fax: +39.02.95.917.801
Mail: sales@ortea.com

www.ortea.com